

---

## Battery Info

Capacity:	148Wh, 10Ah/14.8V (Equivalent to 40,000mAh, 3.7V)	Cell Chemistry:	Lithium-ion
Lifecycle:	500 cycles to 80%+ capacity	AC Power:	150W (Surge 300W)

---

## Output

Inverter Type:	Modified Sine Wave	AC Output:	2 x 110V, 150W (300W Max)
USB-A Output:	2 x 5V, 2.1A (Max)	DC Output:	3 x 12-16.8V, 10A, 180W Max
USB-C Output:	1 x 5V, 2A, 9V/12V/15V, 2A (Max), 30W	Car Output:	1 x 12V, 5A 150W Max
Quick Charge 3.0 Output:	1 x 5V/9V, 2A or 12V, 1.5A, 18W		

---

## LED Light

Power	3W	Modes	Weak, Strong, SOS
-------	----	-------	-------------------

---

## Recharge

Input Port:	DC 5521	AC Adaptor:	DC 15V, 2A, 30W
Solar Input:	DC 7-24V, 2A, 30W Max		

---

## General

Dimensions:	6.9 x 4.1 x 4.3 in (17 x 10.5 x 11.5cm)	Weight:	4.0 lbs (1.8 kg)
Operating Temperature:	32°F-104°F (0°C-40°C)	Storage Temperature:	32°F-104°F (0°C-40°C)
Certification:	CE, FCC, ROHS	Product Warranty:	2-year Product Warranty

---

## In The Box

1 x P201 Portable Power Station, 1 x AC Adaptor (AC-DC 5521), 1 x Car Charging Cable, 1 x Car Cigarette Lighter Adaptor, 1 x User Manual

